



Electrical and Computer Engineering Department  
**University of Maryland**  
 College Park, MD 20742-3285

Glenn L. Martin Institute of Technology ♦ A. James Clark School of Engineering

Dr. Charles B. Silio, Jr.  
 Telephone 301-405-3668  
 Fax 301-314-9281  
 silio@umd.edu

**ENEE 350 Homework Set 7**

Programming Project 2

(Due: Class 19, Wed., July 1, 2009)

Write, assemble and run successfully on the simulator a Mac-1 subroutine **lgneg(n,x)** that returns in the AC the address of the integer possessing the algebraically largest negative value along the real line among the *n* integers in the array whose starting address is *x*. The largest negative value on the real line is the farthest right value to the left of zero. If there are no negative values among the *n* elements to be processed, then return -1 which is equivalent to the unsigned integer address 65535, clearly not a valid memory address. If there are two or more array entries that equally satisfy the requirements, return the address of the one with the highest address. Your subroutine should be tested with the main program shown below, which defines how the parameters are passed.

/main program				/continued from below halt		
	EXTRN	lgneg		data	57	
ans1	RES	1			0	
ans2	RES	1			129	
ans3	RES	1			34	
n1		6			8	
n2		10			3	
n3		5			-29	
start	loco	4020			-15	
	swap	/initialize sp			-2	
	loco	n1			-347	
	push	/push address n1			-3	
	loco	data			6	
	push	/push array start address			35	
one	call	lgneg			-413	
	stod	ans1		END	start	
	insp	2				
	loco	n2 /push address n2				
	push					
	loco	data				
	addd	(4)				
	push	/push array start address				
two	call	lgneg				
	stod	ans2				
	insp	2				
	loco	n3 /push address n3				
	push					
	loco	data				
	addd	(9)				
	push	/push array start address				
three	call	lgneg				
	stod	ans3				
	insp	2				
	halt					
	/data array continues here but					
	/ is shown in the above right hand column					

Hand in a copy of the main program symbolic assembly listing, the subroutine symbolic assembly listing, the contents of (macro) memory after "load main sub" (i.e., of main.abs) before execution of the program, and the contents of memory after execution of the program. Highlight and comment upon the final answers. Specify what values are contained in the addresses specified by ans1, ans2, and ans3.